


DC/DC Converter TSR 0.5 Series


EMI Consideration

Suggested filter to comply with EN 55032 Radiated Emissions Class A limits

TSR 0.5 Series fulfill radiated Emissions Class A without external components.

Suggested filter to comply with EN 55032 Conducted Emissions Class A limits







| Suggested components to comply with EN 55032 Conducted Class A limits | | |
|---|---------------------------|-----------------------------------|
| Model | C1, C2 | ដ |
| TSR 0.5-xxxx | 4.7 μF / 50 V / 1206 MLCC | 3.3 μH / 4 A / 60 mΩ 744774033 |

Suggested filter to comply with EN 55032 Radiated Emissions Class B limits

TSR 0.5 Series fulfill radiated Emissions Class B without external components.

Suggested filter to comply with EN 55032 Conducted Emissions Class B limits





| Suggested components to comply with EN 55032 Conducted Class B limits | | |
|---|---------------------------|------------------------------------|
| Model | C1, C2, C3 | L1 |
| TSR 0.5-xxxx | 4.7 μF / 50 V / 1206 MLCC | 10 μH / 2.2 A / 100 mΩ 74477410 |